

# Фильтрующие вентиляторы ELDON EF

## Технические характеристики



**Архангельск** (8182)63-90-72  
**Астана** (7172)727-132  
**Астрахань** (8512)99-46-04  
**Барнаул** (3852)73-04-60  
**Белгород** (4722)40-23-64  
**Брянск** (4832)59-03-52  
**Владивосток** (423)249-28-31  
**Волгоград** (844)278-03-48  
**Вологда** (8172)26-41-59  
**Воронеж** (473)204-51-73  
**Екатеринбург** (343)384-55-89  
**Иваново** (4932)77-34-06

**Ижевск** (3412)26-03-58  
**Иркутск** (395)279-98-46  
**Казань** (843)206-01-48  
**Калининград** (4012)72-03-81  
**Калуга** (4842)92-23-67  
**Кемерово** (3842)65-04-62  
**Киров** (8332)68-02-04  
**Краснодар** (861)203-40-90  
**Красноярск** (391)204-63-61  
**Курск** (4712)77-13-04  
**Липецк** (4742)52-20-81

**Киргизия** (996)312-96-26-47

**Магнитогорск** (3519)55-03-13  
**Москва** (495)268-04-70  
**Мурманск** (8152)59-64-93  
**Набережные Челны** (8552)20-53-41  
**Нижний Новгород** (831)429-08-12  
**Новокузнецк** (3843)20-46-81  
**Новосибирск** (383)227-86-73  
**Омск** (3812)21-46-40  
**Орел** (4862)44-53-42  
**Оренбург** (3532)37-68-04  
**Пенза** (8412)22-31-16

**Россия** (495)268-04-70

**Пермь** (342)205-81-47  
**Ростов-на-Дону** (863)308-18-15  
**Рязань** (4912)46-61-64  
**Самара** (846)206-03-16  
**Санкт-Петербург** (812)309-46-40  
**Саратов** (845)249-38-78  
**Севастополь** (8692)22-31-93  
**Симферополь** (3652)67-13-56  
**Смоленск** (4812)29-41-54  
**Сочи** (862)225-72-31  
**Ставрополь** (8652)20-65-13

**Казахстан** (772)734-952-31

**Сургут** (3462)77-98-35  
**Тверь** (4822)63-31-35  
**Томск** (3822)98-41-53  
**Тула** (4872)74-02-29  
**Тюмень** (3452)66-21-18  
**Ульяновск** (8422)24-23-59  
**Уфа** (347)229-48-12  
**Хабаровск** (4212)92-98-04  
**Челябинск** (351)202-03-61  
**Череповец** (8202)49-02-64  
**Ярославль** (4852)69-52-93

# Thermal Management Ventilation Range

## High flow filter fan | EF

IP 54 | TYPE 12



**Description:**

Filter fan for forced ventilation. nVent HOFFMAN filter fans save time on installation as they are installed with a click-in system without screws. The hinged front cover can be easily opened for quick and easy filter replacement. The airflow direction and the connection position can easily be changed.

**Material:**

Front cover manufactured from injection-moulded thermoplastic, self-extinguishing, UL94V0.

**Temperature range:**

-40 °C to +55 °C.

**Protection:**

IP 54 | TYPE 12.

**Finish:**

RAL 7035.

**Pack quantity:**

One fan with filter.



## IP 54 | TYPE 12

230 V AC, 50/60 Hz

Unimpeded airflow (m³/h)	EF+EFA Air flow (m³/h)	Filter mat (EN779)	Filtration efficiency (%)	Service life L10 (40°C)(h)	Bearing type	Noise (dB)	Item no.
19/24	12/14	G4	>90	52.500	Sleeve	33	EF100R5
61/67	44/50	G4	>90	37.500	Sleeve	44	EF200R5
98/108	73/80	G4	>90	37.500	Sleeve	40	EF220R5
125/138	93/102	G4	>90	40.000	Ball	40	EF250R5
223/247	201/223	G4	>90	40.000	Ball	42	EF300R5
480/480	370/370	G3	80-90	40.000	Ball	54	EF500R5
640/653	445/445	G3	80-90	40.000	Ball	63	EF600R5
845/875	560/625	G3	80-90	40.000	Ball	66	EF700R5

230 V AC, 50/60 Hz

Cut-out (mm)	Weight (kg)	Connection	Current (A)	Power (W)	Fuse (A)	Item no.
92 x 92	0.55	310 mm cable	0.07/0.06	12/11	6	EF100R5
125 x 125	0.80	Terminal strip	0.12/0.18	19/18	6	EF200R5
177 x 177	1.05	Terminal strip	0.12/0.18	19/18	6	EF220R5
223 x 223	1.45	Spring type	0.12/0.10	18/17	6	EF250R5
223 x 223	1.90	Spring type	0.32/0.26	45/39	6	EF300R5
291 x 291	3.85	Spring type	0.30/0.36	80/100	6	EF500R5
291 x 291	4.05	Spring type	0.51/0.66	120/160	6	EF600R5
291 x 291	4.50	Spring type	0.59/0.88	140/197	6	EF700R5

115 V AC, 50/60Hz

Unimpeded airflow (m³/h)	EF+EFA Air flow (m³/h)	Filter mat (EN779)	Filtration efficiency (%)	Service life L10 (40°C)(h)	Bearing type	Noise (dB)	Item no.
19/24	12/14	G4	>90	55.000	Sleeve	33	EF100-115R5
61/67	44/50	G4	>90	40.000	Sleeve	44	EF200-115R5
98/108	73/80	G4	>90	40.000	Sleeve	40	EF220-115R5
125/138	93/102	G4	>90	42.500	Ball	43	EF250-115R5
223/247	201/223	G4	>90	40.000	Ball	46	EF300-115R5
480/480	370	G3	80-90	40.000	Ball	52	EF500-115R5
640/653	445	G3	80-90	40.000	Ball	64	EF600-115R5
845/875	625	G3	80-90	40.000	Ball	69	EF700-115R5

115 V AC, 50/60Hz

Cut-out (mm)	Weight (kg)	Connection	Current (A)	Power (W)	Fuse (A)	Item no.
92 x 92	0.55	310 mm cable	0.15/0.15	12/11	6	EF100-115R5
125 x 125	0.80	Terminal strip	0.24/0.23	20/20	6	EF200-115R5
177 x 177	1.05	Terminal strip	0.24/0.23	20/20	6	EF220-115R5
223 x 223	1.45	Spring type	0.25/0.25	18/17	6	EF250-115R5
223 x 223	1.90	Spring type	0.50/0.50	40/40	6	EF300-115R5
291 x 291	3.85	Spring type	0.66/0.80	75/90	6	EF500-115R5
291 x 291	4.10	Spring type	0.96/1.40	110/160	6	EF600-115R5
291 x 291	4.50	Spring type	1.23/1.71	140/195	6	EF700-115R5

24 V DC

Unimpeded airflow (m³/h)	EF+EFA Air flow (m³/h)	Filter mat (EN779)	Filtration efficiency (%)	Service life L10 (40°C)(h)	Bearing type	Noise (dB)	Item no.
19/24	12/14	G4	>90	70.000	Ball	33	EF100-24R5
61/67	44/50	G4	>90	62.500	Ball	44	EF200-24R5
98/108	73/80	G4	>90	62.500	Ball	40	EF220-24R5
125/138	93/102	G4	>90	70.000	Ball	40	EF250-24R5
223/247	201/223	G4	>90	80.000	Ball	42	EF300-24R5

24 V DC

Cut-out (mm)	Weight (kg)	Connection	Current (A)	Power (W)	Fuse (A)	Item no.
92 x 92	0.25	310 mm cable	0.10	2.40	6	EF100-24R5
125 x 125	0.45	310 mm cable	0.21	5.00	6	EF200-24R5
177 x 177	0.70	310 mm cable	0.21	5.00	6	EF220-24R5
223 x 223	1.40	Spring type	0.20	4.70	6	EF250-24R5
223 x 223	1.45	Spring type	0.50	12.00	6	EF300-24R5



Архангельск (8182)63-90-72  
Астана (7172)727-132  
Астрахань (8512)99-46-04  
Барнаул (3852)73-04-60  
Белгород (4722)40-23-64  
Брянск (4832)59-03-52  
Владивосток (423)249-28-31  
Волгоград (844)278-03-48  
Вологда (8172)26-41-59  
Воронеж (473)204-51-73  
Екатеринбург (343)384-55-89  
Иваново (4932)77-34-06

Ижевск (3412)26-03-58  
Иркутск (395)279-98-46  
Казань (843)206-01-48  
Калининград (4012)72-03-81  
Калуга (4842)92-23-67  
Кемерово (3842)65-04-62  
Киров (8332)68-02-04  
Краснодар (861)203-40-90  
Красноярск (391)204-63-61  
Курск (4712)77-13-04  
Липецк (4742)52-20-81

Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13  
Москва (495)268-04-70  
Мурманск (8152)59-64-93  
Набережные Челны (8552)20-53-41  
Нижний Новгород (831)429-08-12  
Новокузнецк (3843)20-46-81  
Новосибирск (383)227-86-73  
Омск (3812)21-46-40  
Орел (4862)44-53-42  
Оренбург (3532)37-68-04  
Пенза (8412)22-31-16

Россия (495)268-04-70

Пермь (342)205-81-47  
Ростов-на-Дону (863)308-18-15  
Рязань (4912)46-61-64  
Самара (846)206-03-16  
Санкт-Петербург (812)309-46-40  
Саратов (845)249-38-78  
Севастополь (8692)22-31-93  
Симферополь (3652)67-13-56  
Смоленск (4812)29-41-54  
Сочи (862)225-72-31  
Ставрополь (8652)20-65-13

Казахстан (772)734-952-31

Сургут (3462)77-98-35  
Тверь (4822)63-31-35  
Томск (3822)98-41-53  
Тула (4872)74-02-29  
Тюмень (3452)66-21-18  
Ульяновск (8422)24-23-59  
Уфа (347)229-48-12  
Хабаровск (4212)92-98-04  
Челябинск (351)202-03-61  
Череповец (8202)49-02-64  
Ярославль (4852)69-52-93